

# **LP-400**

### **Product Description**

LP-400 is the latest fingerprint time and attendance terminal of ZKSoftware with built-in thermal printer. LP-400 features the fastest commercial-based fingerprint matching algorithm and ZK high-performance, high-image quality optical fingerprint sensor. The 3" TFT can display more information vividly, including fingerprint image quality and verification result etc. TCP/IP communication is standard and make sure the data transmission between terminal and PC can be easily done within several second.

#### Standard function

























### Optional function











## **Features**

- Built-in thermal printer.
- Color TFT screen with GUI interface for easy use.
- One second user recognition.
- Stores 3,000 templates and 100,000 transactions.
- Reads fingerprint and/or PINs.
- Optional integrated proximity or smart card reader.
- Built in serial and Ethernet ports.
- Built-in USB port allows for manual data transfer when network isn't available.
- Built-in bell scheduling.
- ✓ Audio-visual indicators for acceptance and rejection of valid/invalid fingers.
- SDK available for OEM partners and software developers.





## **Specifications**

#### Capacity

Templates 3.000 Transactions 100,000

#### Hardware

Platform ZEM510

CPU 32bit ZK6001 Microprocessor 400MHz
Memory 32M RAM, 256M Flash

Fingerprint Sensor ZK optical sensor

Printer Thermal

#### Display

LCD TFT Screen 3 inch
LED Indicator Red and Green

#### Environment

Oper. Temp 0°-45°C Oper. Humidity 20%-80%

#### Power

Power 12V DC, 3A

### Communication

Comm. Port Ethernet
Pendrive USB-host

#### Fingerprint Algorithm

Type ZK Finger 10.0 Identification <=2 seconds 
Verification <=1 second 
FRR < 1% 
FAR <=0.0001%

#### Languages

Available All European languages

Maximum 7

Voices Allowed

#### Keypad

Type Buttons keypad

#### **Dimensions**

Dimensions 171x284x120mm (L x W x D)
Weight 2.2kg

#### Firmware

O.S Linux Applications T&A

SDK Standard SDK

## **Connectivity diagram**

