

# inPulse+ Multi-Biometric Finger Vein Standalone Access Control Terminal



inPulse+ is a multi-biometric reader capable of capturing and processing finger vein and fingerprint biometric data at the same time. Ergonomic, intuitive and highly secured, inPulse+ leads us to a new era of enhancing security with biometrics. Its infra-red rays illuminate the vein pattern which is then converted into a biometric template. Both the vein and fingerprint templates are then stored in the database for subsequent matching.



https://smartel.ua

## **Features**



### Specifications (G: GL Exclusive Feature)

#### Capacity

· · ·	
Ger Finger Veins	1,500
G Fingerprints	1,500
Cards	2,000
Transactions	100,000

#### Communication

GTCP/IP USB Host Wiegand Input / Output Security Relay Box

#### Access Control Interface

Lock Relay Output Alarm Output / Auxiliary Input Exit Button / Door Sensor Doorbell Output


#### Hardware

- G 1.2GHz High Speed CPU
- G Memory 128MB RAM / 256MB Flash ZK Fingerprint Sensor
- 2.8 Inches TFT-LCD Touch Screen 125KHz EM Reader / Mifare (Optional) Hi-Fi Voice & Indicator Tamper Switch Alarm

#### **Standard Functions**

Access Levels / Groups / Holidays DST / Bell Schedule Duress Mode (Password) Anti-Passback Record Query Custom Wallpaper & Screen Saver

## **Dimensions (mm)**





ZKTeco Inc.



© Copyright 2016. ZKTeco Inc. ZKTeco Logo is a registered trademark of ZKTeco or a related company. All other product and company names mentioned are used for identification purposes only and may be the trademarks of their respective owners. All specifications are subject to change without notice. All rights reserved.



https://smartel.ua

#### Special Functions

Gultiple Biometric Verification Modes ZK Encrypted Card (Optional)

#### Compatibility

Wiegand Slave Reader ZKBioSecurity Software

#### Additional Info

Working Temperature: -10 °C ~ 50 °C Dimensions: 201.7 × 85 × 102.7 mm. ZKVein v3.0 & ZKFinger v10.0 Algorithms Finger Vein & Fingerprint: FAR $\leq$ 0.0001% FRR $\leq$ 0.01% Package Includes 12V 3A Power Supply

#### Power

Operating Voltage 12V DC Current Draw < 500mA

## Configuration

